



彩卡正面

Features:

- Multipurpose EDC Keychain
- Multi-function flashlight
- Type-C charging
- Counterfeit detecting, signal light
- Max output up to 500 lumens
- Using a CREE XP-G3 LED, RGB color lamp, 365nm UV lamp
- Side switch, easy to operate
- Built-in 120mAh lithium polymer battery.

FL1 STANDARD	TURBO	HIGH	MEDIUM	LOW	ECO	COLORED LIGHT	FLASH
	500LM	200LM	100LM	35LM	1LM	150LM	150LM
	10min	20min	35min	1.5h	15h	/	/
	1800cd	The above data is measured in the laboratory according to the measurement method described in the international flashlight measurement standard ANSI / NEMA, FL1, using JETBeam built-in 120mAh lithium battery in the laboratory, different batteries or use environment may affect the above data.					
	85m						
	1.5m						
	2m						

Operation:

White light: Short press On/Off.
When the light is on, A long press of the side switch changes the various brightness modes from Eco-low-middle-high.
When the light is off, A long press of the side switch to access the Turbo (Keep pressing for 30 seconds long will be turned off the light), release to turn off the light.

Colored light: Double-click to turn on, single click to turn off. Power on state, long press to switch mode: red, green and blue-warning flash-sequential light-beacon

UV lamp: Three clicks to turn on, one click to turn off
All mode have memory function.

Lock / Unlock
Lockout: With UV light on, press and hold the power button for 8 seconds until the light flashes three times and then goes off.
Unlock: In Lock mode, press and hold the power button for four seconds to turn on the light and back to the last used output of the white LED.

Charging function: TYPE-C charging. Lights up in red when charging, and lights up in green when fully charged. The full charge time is about 40 minutes.

Shenzhen JETBeam Electronic Technology Co.,Ltd
Add: 3/F, Building 2, Dunbei Industrial Area, Dalang South Road, Longhua New District, Shenzhen, 518109, China
E-mail: info@jetbeamlight.com
Web: www.jetbeamlight.com

6 957883 825494
MADE IN CHINA

产品特点:

- 多用途EDC钥匙灯
- 多用途辅助灯，一物多用
- TYPE-C直充
- 验钞、安全警示
- 最高500流明超高亮度输出
- 采用CREE XP-G3 LED, RGB彩灯, 365nm UV灯
- 侧按开关, 方便调节
- 内置120mAh 锂聚合物电池

FL1 STANDARD	极亮	高亮	中亮	低亮	月光	彩光	闪烁
	500LM	200LM	100LM	35LM	1LM	150LM	150LM
	10min	20min	35min	1.5h	15h	/	/
	1800cd	以上数据是按照国际电筒测量标准ANSI/NEMA, FL1所述之测量方法, 使用JETBeam 内置120mAh锂电池在实验室内测量所得, 不同电池或使用环境可能会对以上数据产生影响。					
	85m						
	1.5m						
	2m						

操作方法:

白光: 短按开/关机。开机状态: 长按切换档位: 月光-低-中-高
关机状态下: 长按进入瞬时极亮档(超过30S关机), 松手退出

彩光: 双击开机, 单击关机。开机状态, 长按切换档位: 红-绿-蓝-警闪-流水灯-信标

UV灯: 三击开机, 单击关机

所有档位带记忆。

锁键与解锁: 打开UV灯后, 长按按键8秒UV灯闪烁3次锁机完成。锁机状态下, 长按按键4秒解锁并点亮白光记忆档

充电功能: 采用TYPE-C充电。充电时亮红灯, 充满电时亮绿灯。充满时间大约40分钟

深圳市杰特明电子科技有限公司
咨询热线: +86-0755-28077748
销售邮箱: info@jetbeamlight.com
网 址: www.jetbeamlight.com
公司地址: 广东省深圳市龙华新区大浪南路墩背工业区二栋三楼
邮 编: 518109

彩卡背面

尺寸: 154x122mm

材质: 350g双铜纸

工艺: 双面彩色印刷, 过哑膜和局部UV,对折线处做压痕

备注: 边框无需印刷, 材质需符合ROHS标准

■ C100M70Y0K0